1A Ultra-Low Noise,

High PSRR LDO for RF and Analog Circuits

General Description

The ET5A8XX series of low-dropout, low-power linear regulators offer up to 1000mA with PMOS pass transistor. The device offers low noise, high PSRR, low quiescent current and very good line/load transients, suitable for RF applications and analog circuits.

The ET5A8XX is stable with a 1μF input and 1μF ceramic output capacitor, and uses a precision voltage reference and feedback loop to achieve accuracy of 1.5%.

It is in small DFN6 (2.0mm × 2.0mm), DFN8 (1.2mm × 1.6mm), SOT23-5 (1.6mm × 2.9mm) package, which is ideal for small form factor portable equipment such as wireless handsets and PDAs.

Features

- Wide Input Voltage Range from 1.9V~5.5V
- Output Voltage: 1.8V, 2.2V, 2.3V, 2.4V, 2.45V, 2.5V, 2.6V, 2.7V, 2.8V, 3.0V, 3.3V and etc.
- Output Current up to 1A
- Very Low I_Q of 25μA Typical
- Shutdown Current of 0.1μA Typical
- Low Dropout Are Typical 280mV at 1A, 3.0V output
- Ultra-low Noise Are Typical 10μVrms (I_{OUT} = 200mA) @V_{OUT} = 3V
- Very High PSRR Are 90dB at 1kHz, 42dB at 1MHz @V_{OUT} = 3V
- Excellent Line/Load Transient Response
- Built-in ILIMIT Protection and Thermal Shutdown Circuit
- Built-in Auto Discharge Function
- Part No. and Package Information

Part No.	Package	Packing Option	MSL
ET5A8XXYB	DFN6 (2.0mm × 2.0mm)	Tape and Reel, 3K/Reel	1
ET5A8XXY1B	DFN8 (1.2mm × 1.6mm)	Tape and Reel, 3K/Reel	1
ET5A8XXS5B	SOT23-5 (1.6mm × 2.9mm)	Tape and Reel, 3K/Reel	3


Applications

- Smart Phones and Cellular Phones
- PDAs
- Digital Still Cameras
- Portable Instrument

Mark Specification Label

Part No.	Marking		Output Voltage
	YB (DFN6)	S5B (SOT23-5)	
ET5A818	5A8C	A8CB	1.8V
ET5A822	5A8Q	A8QB	2.2V
ET5A823	5A8e	A8eB	2.3V
ET5A824	5A8W	A8WB	2.4V
ET5A8245	5A8f	A8fB	2.45V
ET5A825	5A8F	A8FB	2.5V
ET5A826	5A8g	A8gB	2.6V
ET5A827	5A8P	A8PB	2.7V
ET5A828	5A8D	A8DB	2.8V
ET5A830	5A8G	A8GB	3.0V
ET5A833	5A8E	A8EB	3.3V

Pin Configuration



DFN6 (ET5A8XXYB) DFN8 (ET5A8XXY1B) SOT23-5 (ET5A8XXS5B)

Top View

Figure1. Pin Configuration

Pin Function

Pin No.			Pin Name	Pin Description
DFN6	DFN8	SOT23-5		
1	1	5	OUT	Output Pin. A 1μF low-ESR Capacitor Should be Connected to This Pin to Ground.
2, 5	2, 3, 4, 7	4	NC	No Connect
3	5	2	GND	Ground
4	6	3	EN	Enable Control Input, Active High. Do Not Leave EN Floating
6	8	1	IN	Supply Input Pin. Must be Closely Decoupled to GND with a 1μF Ceramic Capacitor
-	-	/	Thermal Pad	Thermal Pad (DFN6), Connect to GND Plane for Better Power Dissipation

Block Diagram




Figure2. Block Diagram

Functional Description

Input Capacitor

A 1μF ceramic capacitor is recommended to connect between IN and GND pins to decouple input power supply glitch and noise. The amount of the capacitance may be increased without limit. This input capacitor must be located as close as possible to the device to assure input stability and less noise. For PCB layout, a wide copper trace is required for both IN and GND. The input capacitor should be at least equal to, or greater than, the output capacitor for good load transient performance.

Output Capacitor

An output capacitor is required for the stability of the LDO. The recommended output capacitance is from 1μF to 10μF, Equivalent Series Resistance (ESR) is from 5mΩ to 100mΩ, and temperature characteristics are X7R or X5R. Higher capacitance values help to improve load/line transient response. The output capacitance may be increased to keep low undershoot/overshoot. Place output capacitor as close as possible to OUT and GND pins. With a reasonable PCB layout, the single 1μF ceramic output capacitor can be placed up to 10cm away from the ET5A8XX device.

Remote Output Capacitor Placement

The ET5A8XX requires at least a 1μF capacitor at the OUT pin, but there are no strict requirements about the location of the capacitor in regards the OUT pin. In practical designs, the output capacitor may be located up to 10cm away from the LDO.


Low Quiescent Current

The ET5A8XX, consuming only 25μA quiescent current, provides great power saving in portable and low power applications.


On/Off Input Operation

The ET5A8XX is turned on by setting the EN pin higher than V_{IH} threshold, and is turned off by pulling it lower than V_{IL} threshold. If this feature is not used, the EN pin should be tied to IN pin to keep the regulator output on at all time.

During soft-start time, in order to achieve a rapid increase in output voltage to reach the set value, the ET5A8XX will short-circuit the filter resistor for approximately 0.5ms. Therefore, it is required that V_{IN} be greater than V_{OUT} set value within 0.5ms upon enable or be established completely before the enable signal is issued.



V_{EN} power on before V_{IN}



V_{IN} and V_{EN} power on at same time

Figure3. On/Off Input Operation

High PSRR and Low Noise

The ET5A8XX, with PSRR of 90dB at 1KHz. It is suitable for most of these applications that require high PSRR and low noise.

Fast Transient Response

The ET5A8XXs fast transient response from 0 to 1A provides stable voltage supply for fast DSP and GSM chipset with fast changing load.

Dropout Voltage

Generally speaking, the dropout voltage often refers to the voltage difference between the input and output voltage. The ET5A8XX internal circuitry is not fully functional until V_{IN} is at least 1.9V. The output voltage is not regulated until V_{IN} has reached at least the greater of (V_{OUT} + V_{DROP}).

Current Limit Protection

When output current at the OUT pin is higher than current limit threshold or the OUT pin is short-circuiting to GND, the current limit protection will be triggered and clamp the output current to approximately 1.5A to prevent over-current and to protect the regulator from damage due to overheating.

Output Automatic Discharge

The ET5A8XX output employs an internal 90Ω (typical) pull-down resistance to discharge the output when the EN pin is low, and the device is disabled.

Thermal Overload Protection

Thermal shutdown disables the output when the junction temperature rises to approximately 155°C which allows the device to cool. When the junction temperature cools to approximately 130°C, the output circuitry enables. Based on power dissipation, thermal resistance, and ambient temperature, the thermal protection circuit may cycle on and off. This thermal cycling limits the dissipation of the regulator and protects it from damage as a result of overheating.

The thermal shutdown circuitry of the ET5A8XX has been designed to protect against temporary thermal overload conditions. The TSD circuitry was not intended to replace proper heat-sinking. Continuously running the ET5A8XX device into thermal shutdown may degrade device reliability.

Absolute Maximum Ratings

Symbol	Item		Rating	Unit
V_{IN}	IN Voltage		-0.3 to 6.0	V
V_{EN}	Input Voltage (EN Pin)		-0.3 to 6.0	V
V_{OUT}	Output Voltage		-0.3 to V_{IN} + 0.3	V
P_D	Maximum Power Consumption(1)	DFN6	1200	mW
		DFN8	1200	
		SOT23-5	500	
I_{MAX}	Maximum Load Current		1000	mA
T_J	Operating Junction Temperature		-40 to 150	°C
T_{STG}	Storage Temperature		-65 to 150	°C
T_{SLOD}	Lead Temperature (Soldering, 10 sec)		260	°C
V_{ESD}	HBM (JEDEC JS-001)		±2000	V
	CDM (JEDEC JS-002)		±500	V

Note1: Rating at mounting on a board (PCB board dimension: 40mm × 40mm (4layer), copper: 1OZ).

Recommended Operating Conditions

Symbol	Item	Rating	Unit
V_{IN}	Input Voltage(2)	1.9 to 5.5	V
I_{OUT}	Output Current	1 to 1000	mA
T_A	Operating Ambient Temperature	-40 to 85	ºC
C_{IN}	Effective Input Ceramic Capacitor Value	0.68 to 10	μF
C_{OUT}	Effective Output Ceramic Capacitor Value	0.68 to 10	μF
ESR	Input and Output Capacitor Equivalent Series Resistance (ESR)	5 to 100	mΩ

Note2: In order to achieve high performance of PSRR, it is recommended that the V_{IN} needs to be no smaller than (V_{OUT} + 0.5V).

Electrical Characteristics

(V_{EN} = V_{IN} = V_{OUT} + 1V, C_{IN} = 1μF, C_{OUT} = 1μF. Typical values are at T_A = 25°C, unless otherwise stated)

Symbol	Parameters	Test Conditions		Min	Typ	Max	Unit
V_{IN}[(2)]	Input Voltage Range			1.9		5.5	V
V_{OUT}	Output Voltage Accuracy	V_{IN} = $V_{OUT(NOM)}$ + 1V, I_{OUT} = 1mA, -40°C < T_A < 85°C		-1.5		1.5	%
I_{LOAD}	Load Current			1000			mA
V_{DROP}	Dropout Voltage	I_{OUT} = 500mA	V_{OUT} = 1.8V		182	242	mV
			V_{OUT} = 2.2V		155	215	
			V_{OUT} = 2.3V		151	211	
			V_{OUT} = 2.4V		147	207	
			V_{OUT} = 2.45V		145	205	
			V_{OUT} = 2.5V		142	202	
			V_{OUT} = 2.6V		139	199	
			V_{OUT} = 2.7V		137	197	
			V_{OUT} = 2.8V		135	195	
			V_{OUT} = 3.0V		130	190	
			V_{OUT} = 3.3V		110	170	
		I_{OUT} = 1000mA	V_{OUT} = 1.8V		378	488	
			V_{OUT} = 2.2V		330	440	
			V_{OUT} = 2.3V		322	432	
			V_{OUT} = 2.4V		314	424	
			V_{OUT} = 2.45V		308	418	
			V_{OUT} = 2.5V		304	414	
			V_{OUT} = 2.6V		300	410	
			V_{OUT} = 2.7V		295	405	
			V_{OUT} = 2.8V		290	400	
			V_{OUT} = 3.0V		280	390	
			V_{OUT} = 3.3V		260	370	
Reg_{LINE}	Line Regulation	V_{IN} = V_{OUT} + 1V to 5.5V, I_{OUT} = 1mA			0.01	0.1	%/V
Reg_{LOAD}	Load Regulation	V_{IN} = V_{OUT} + 0.5V, I_{OUT} = 1mA to 1000mA			50	70	mV
I_{Q_ON}	Input Quiescent Current	I_{OUT} = 0mA			25	35	μA
I_{Q_OFF}	Input Shutdown Quiescent Current	V_{EN} = 0V			0.1	1	μA
I_{LIMIT}	Current Limit	T_A = 25°C		1.05	1.5	2.0	A
I_{SHORT}	Short Current Limit	V_{OUT} = 0V, T_A = 25°C		450	650	850	mA

Electrical Characteristics (Continued)

(V_{EN} = V_{IN} = V_{OUT} + 1V, C_{IN} = 1μF, C_{OUT} = 1μF. Typical values are at T_A = 25°C, unless otherwise stated)

Symbol	Parameters	Test Conditions	Min	Typ	Max	Unit
PSRR(3)	Power Supply Rejection Ratio V_{OUT} = 3.0V	f = 100Hz, I_{OUT} = 20mA		90		dB
		f = 1kHz, I_{OUT} = 20mA		90		dB
		f = 100kHz, I_{OUT} = 20mA		60		dB
		f =1MHz, I_{OUT} = 20mA		42		dB
e_N(3)	Output Noise Voltage V_{OUT} = 3.0V	BW =10 Hz to 100kHz, I_{OUT} = 1mA		13		μV_{RMS}
		BW =10 Hz to 100kHz, I_{OUT} = 200mA		10		μV_{RMS}
V_{IH}	EN Input Logic High Voltage	V_{IN} = 5.5V, I_{OUT} = 1mA, V_{EN} Rising Until the Output is Enabled	0.84			V
V_{IL}	EN Input Logic Low Voltage	V_{IN} = 5.5V, V_{EN} Falling Until the Output is Disabled			0.4	V
I_{EN}	EN Input Current	V_{EN} = 0V to 5.5V		10		nA
R_{LOW}	Output Discharge FET Rdson	V_{EN} < 0.4V, V_{OUT} = 3.0V	70	90	120	Ω
V_{TRLN}(3)	Line transient	V_{IN} = V_{OUT} + 1V to 5.5V in 10μs, I_{OUT} = 1mA, T_A = 25°C			+25	mV
		V_{IN} = 5.5V to V_{OUT} + 1V in 10μs, I_{OUT} = 1mA	-25			mV
V_{TRLD}(3)(4)	Load transient	I_{OUT} = 1mA to 1000mA in 10μs		50	70	mV
		I_{OUT} = 1000mA to 1mA in 10μs		70	90	mV
t_{ON}	Output Turn-on Time	From V_{EN} > V_{IH} to V_{OUT} = 95% of $V_{OUT(NOM)}$	300	500	700	μs
T_{SHDN}	Thermal Shutdown threshold(3)	T_J rising		155		°C
T_{HYS}	Thermal Shutdown Hysteresis(3)	T_J Falling from Shutdown		25		°C

Note3: Guaranteed by design and characterization. not a FT item.

Note4: Due to PD limitations, during the test of the SOT package circuit, V_{IN} = V_{OUT} + 0.5V.

Application Circuit






Figure4. Application Circuit

Typical Characteristics


(V_{OUT} = 2.5V, V_{EN} = V_{IN} = V_{OUT} + 1V, C_{IN} = 1μF, C_{OUT} = 1μF. Typical values are at T_A = 25°C, unless otherwise stated.)




Output Voltage VS Temperature




Supply Current VS Temperature




Dropout Voltage VS Output Current



Output Voltage VS Input Voltage (I_{OUT} = 1mA)




Output Voltage VS Output Current




PSRR (C_{OUT}=2.2uF，I_{OUT} = 200mA)

Typical Characteristics (Continued)


(V_{OUT} = 2.5V, V_{EN} = V_{IN} = V_{OUT} + 1V, C_{IN} = 1μF, C_{OUT} = 1μF. Typical values are at T_A = 25°C, unless otherwise stated.)



Turn On Speed VS EN Voltage (I_{OUT} = 20mA)




Turn Off Speed VS EN Voltage (I_{OUT} = 20mA)




Line Transient Response

V_{IN} = 3.5V~5.5V, I_{OUT} = 1mA




Line Transient Response

V_{IN} = 5.5V~3.5V, I_{OUT} = 1mA



Load Transient Response

V_{IN} = 3.5V, I_{OUT} = 1mA~1000mA




Load Transient Response


V_{IN} = 3.5V, I_{OUT} = 1000mA~1mA

Typical Characteristics


(V_{OUT} = 3.0V, V_{EN} = V_{IN} = V_{OUT} + 1V, C_{IN} = 1μF, C_{OUT} = 1μF. Typical values are at T_A = 25°C, unless otherwise stated.)




Output Voltage VS Temperature




Supply Current VS Temperature




Dropout Voltage VS Output Current



Output Voltage VS Input Voltage (I_{OUT} = 1mA)




Output Voltage VS Output Current




PSRR (I_{OUT} = 20mA)

Typical Characteristics (Continued)


(V_{OUT} = 3.0V, V_{EN} = V_{IN} = V_{OUT} + 1V, C_{IN} = 1μF, C_{OUT} = 1μF. Typical values are at T_A = 25°C, unless otherwise stated.)



Turn On Speed VS EN Voltage (I_{OUT} = 100mA)




Turn Off Speed VS EN Voltage (I_{OUT} = 100mA)




Line Transient Response

V_{IN} = 4.0V~5.5V, I_{OUT} = 1mA




Line Transient Response

V_{IN} = 5.5V~4.0V, I_{OUT} = 1mA



Load Transient Response

V_{IN} = 4.0V, I_{OUT} = 1mA~1000mA




Load Transient Response


V_{IN} = 4.0V, I_{OUT} = 1000mA~1mA

Recommend PCB Layout


DFN6 (2mm × 2mm)



DFN8 (1.2mm × 1.6mm)




SOT23-5 (1.6mm × 2.9mm)



Package Dimension

DFN6 (2mm × 2mm)




COMMON DIMENSIONS

(Unit: mm)

SYMBOL	MIN	NOM	MAX
A	0.70	0.75	0.80
A1	0.00	0.02	0.05
A3		0.20REF	
b	0.25	0.35	0.45
D	1.90	2.00	2.10
E	1.90	2.00	2.10
D2	0.65	0.80	0.90
E2	1.35	1.50	1.60
e		0.65BSC	
L	0.30	0.35	0.40
k	0.20	--	--

DFN8 (1.2mm × 1.6mm)




COMMON DIMENSIONS

(Unit: mm)

SYMBOL	MIN	NOM	MAX
A	0.40	-	0.50
A1	0.00	-	0.05
A3		0.125REF	
b	0.13	0.18	0.23
D	1.15	1.20	1.25
E	1.55	1.60	1.65
D2	0.25	0.30	0.35
E2	1.25	1.30	1.35
e		0.40BSC	
L	0.15	0.20	0.25

SOT23-5 (1.6mm × 2.9mm)




COMMON DIMENSIONS

(Unit: mm)


SYMBOL	MIN	NOM	MAX
A	-	-	1.45
A1	0.00	-	0.15
b	0.28	0.35	0.50
c	0.08	0.15	0.22
D	2.75	2.9	3.05
e	0.90	0.95	1.00
e1	1.80	1.90	2.00
E	2.60	2.80	3.00
E1	1.45	1.6	1.75
L	0.60REF		
L1	0.30	0.45	0.60

Tape Information


DFN6 (2mm × 2mm)




DFN8 (1.2mm × 1.6mm)




SOT23-5 (1.6mm × 2.9mm)



Marking Information




DFN6
5A8 - Part Number
X - Output Voltage
XXXX- Tracking Number



SOT23-5
A8 & B- Part Number
X - Output Voltage
XXXXX - Tracking Number

Reel Information




Unit: mm


Package Information

Package Type	Tube Dimension	Units/ Tube	Inner Box Dimension	Tube/ Inner Box	Units/ Inner Box	Outer Box Dimension	Inner Boxes/ Outer Box	Units/ Outer Box
1*1	Listed below	10000	200*197* 27mm^3	1	3000	220*415*3 00mm^3	18	54000


Inner Box



Outer Box



Picture of Real Products







Revision History and Checking Table

Version	Date	Revision Item	Modifier	Function & Spec Checking	Package & Tape Checking
0.1	2024-04-02	Preliminary Version	Li huan	Liu yiguo	Liu jiaying
0.2	2024-04-11	Update Format	Wu junyan	Liu yiguo	Liu jiaying
1.0	2025-08-07	Official Version	Yang xiaoxu	Liu yiguo	Liu jiaying
1.1	2025-10-09	Update EC Table	Yang xiaoxu	Liu yiguo	Liu jiaying
1.1.a	2026-01-27	Correct Mistake	Yang xiaoxu	Liu yiguo	Liu jiaying
1.2	2026-02-27	Add Output Voltage and Vdrop	Yu yifan	Yang xiaoxu	Liu jiaying
1.3	2026-06-05	Add 2.5 V Output Typical Application	Zhang zixuan	Yang xiaoxu	Liu jiaying
1.3.a	2026-10-15	Add DFN8 Package	Yang xiaoxu	Yang xiaoxu	Liu jiaying
1.3.b	2026-10-22	Add 2.8 V Output Typical Application	Xu tao	Yang xiaoxu	Liu jiaying